

# **JUKI-750E**

## **DX4-100 with LCD/CRT**

### **& Ethernet SBC**

@Copyright 1999

All Rights Reserved.

Manual first edition Feb.01,1999

The information in this document is subject to change without prior notice in order to improve reliability, design and function and does not represent a commitment on the part of the manufacturer.

In no event will the manufacturer be liable for direct, indirect, special, incidental, or consequential damages arising out of the use or inability to use the product or documentation, even if advised of the possibility of such damages.

This document contains proprietary information protected by copyright. All rights are reserved. No part of this manual may be reproduced by any mechanical, electronic, or other means in any form without prior written permission of the manufacturer.

#### **Trademarks**

JUKI-750E is registered trademarks of ICP Electronics Inc., PC/104 is trademarked of PC/104 Consortium, IBM PC is a registered trademark of International Business Machines Corporation. Intel is a registered trademark of Intel Corporation. AMI is registered trademarks of American Megatrends, Inc. Other product names mentioned herein are used for identification purposes only and may be trademarks and/or registered trademarks of their respective companies.

# Contents

1. Introduction .....	2
2. Installation .....	6
3. Connection .....	12
4. AMI BIOS Setup .....	19
Appendix A. Watch-Dog Timer .....	21
Appendix B. Panel Support List .....	22
Appendix C. I/O Information .....	24

## Introduction

Welcome to the JUKI-750E DX4-100 with LCD/CRT & Ethernet Single Board Computer. The JUKI-750E is an ISA with PC/104 form factor board, which comes equipped with ACC Maple Chipset (includes DX4-100 CPU) and advanced high-performance multi-mode I/O, LCD Controller and Ethernet function, designed for the system manufacturers, integrators, or VARs that want to provide all the performance, reliability, and quality at a reasonable price.

An advanced high performance super I/O function are in the Maple chipset too.. The in chip UARTs are compatible with the NS16C550. The parallel port and IDE interface are compatible with IBM PC/AT and XT architecture's, as well as EPP and ECP.

The LCD/CRT controller is HMC HM86508 which can provide the LCD and CRT display at the same time. The LCD interface connector is a 44-pin 2.0mm pitch type.

The most outstanding feature in the JUKI-750E is built-in PC/104 expansion bus. Based on the PC/104 bus, you could easily install over thousands of PC/104 modules from hundreds' vendors in the world. The JUKI-750E has external power connector that could let it connects with power supply directly. It is more suitable for your standalone applications.

---

## 1.1 Specifications :

The JUKI-750E DX4-100 with LCD/CRT & Ethernet Single Board Computer provides the following specification:

.. **System :**

- **CPU** : ACC Maple, includes DX4-100 CPU
- **DMA channels** : 7
- **Interrupt levels** : 15
- **Real-time clock/calendar** : DS12887/BQ3287 or equivalent chip and quartz oscillator, 128B CMOS memory, powered by lithium battery for over 10 years of data retention.

.. **Memory :**

- **RAM memory** : 1MB to 64MB
- **Shadow RAM memory** :  
System BIOS : 0F0000h ~ 0FFFFFFh

.. **LCD/CRT Interface :**

- **Chipset** : HM86508
- **Resolution** : Support up to 800 x 600 resolution for STN and TFT LCD Flat Panel. And Support 1024x768 256 colors for CRT display.
- **Display Memory** : 1MB on board.

.. **Ethernet Interface :**

- **Chipset** : Realtek RTL-8019 chipset
- **Type** : 10MBps 16-bit Ethernet, Novell NE2000 compatible.

.. **Input/Output :**

- **IDE hard disk drive interface** : Supports up to two IDE hard disk drives. Can be disabled by BIOS Setup.
- **Floppy disk drive interface** : Supports two 2.88 MB, 1.44MB, 1.2MB, 720KB, or 360KB floppy disk drives. Can be disabled by BIOS Setup.

- **Two high speed Series ports** : NS16C550 compatible UARTs with send/receive 16-byte FIFOs, data rates are independently programmable from 115.2K baud down to 50 baud. Modem control circuitry.
- **Multi-mode Parallel Port** :  
 Standard mode - IBM PC/XT, PC/AT, PS/2 compatible bi-directional parallel port.  
 Enhanced mode - Enhanced parallel port ( EPP) compatible with IEEE 1284 specification.  
 High speed mode - Microsoft and Hewlett Packard extended capabilities port ( ECP), compatible with IEEE 1248 specification.
- .. **Industrial features :**
- **Watch-dog timer** : can be set by 1,2,10,20,110,or 220 seconds period. Reset or NMI was generated when CPU did not periodically trigger the timer. Your program use hex 043 and 443 to control the watch-dog and generate a system reset.
- **PC/104 expansion bus** : A 64-pin and 40-pin, industrial embedded-PC bus standard.
- **External power connector** : 8-pin male connector ( Molex 6410 series compatible)
- **Keyboard connector** : A 5-pin header on board and 6-pin mini-DIN keyboard connector is located on the mounting bracket.
- .. **General :**
- **Power Consumption** : +5V @ 1.65A ( DX4-100MHz,32MB RAM)
- **Operating Temperature** : 0° ~ 55°C
- **Humidity** : 5% ~ 95%, non-condense
- **Dimension** : 180mm(W) x 122mm(L), standard AT form factor

---

## 1.2 What You Have

In addition to this *User's Manual*, the JUKI-750E package includes the following items:

- JUKI-750E DX4-100 with LCD/CRT & Ethernet Single Board Computer
- RS-232/Printer Cable
- FDD/HDD Cable
- 6-pin Mini-Din to 5-pin Din Keyboard/Mouse Adapter Cable

# 2

## Installation

This chapter describes how to install the JUKI-750E. At first, the layout of JUKI-750E is shown, and the unpacking information that you should be careful is described. The jumpers and switches setting for the JUKI-750E's configuration, such as CPU type selection, system clock setting, and interrupt IRQ setting for serial ports and parallel port, are also included.

---

### 2.1 JUKI-750E's Layout

< reference next page >







---

## 2.2 CPU Setting for JUKI-750E

### • CPU SPEED SETTING:

The system clock is generated by the AV9155C-02, and the different CPU clock frequency can be selected by JP2 and shown as following table:

JP2	1-2	3-4	5-6
50MHz	CLOSE	OPEN	CLOSE
60MHz	OPEN	OPEN	CLOSE
75MHz	CLOSE	CLOSE	OPEN
100MHz	OPEN	CLOSE	OPEN

---

## 2.3 Watch-Dog Timer

The Watch-Dog Timer is enabled by reading port 443H. It should be triggered before the time-out period ends, otherwise it will assume the program operation is abnormal and will issue a reset signal to start again, or activate NMI to CPU. The Watch-Dog Timer is disable by reading port 843H. The Watch-Dog Timer time-out period can be set 1,2,10,20,110 or 220 sec. by JP4.

### • JP3 : Watch-Dog Active Type Setting

JP3	DESCRIPTION
2-3	RESET WHEN WDT TIME-OUT
1-2	ACTIVATE NMI TO CPU WHEN WDT TIME-OUT
OPEN	DISABLE WDT

### • JP4 : WDT TIME-OUT PERIOD

JP3	1-2	3-4	5-6	7-8
1sec	OPEN	OPEN	CLOSE	OPEN
2sec	OPEN	OPEN	CLOSE	CLOSE
10sec	OPEN	CLOSE	OPEN	OPEN
20sec	OPEN	CLOSE	OPEN	CLOSE
110sec	CLOSE	OPEN	OPEN	OPEN
220sec	CLOSE	OPEN	OPEN	CLOSE

---

## 2.4 DiskOnChip™ Flash Disk

The DiskOnChip™ Flash Disk Chip(DOC) is produced by MSystems. The DOC(MD-2200-xMB) is 32-pin DIP package.

Because the DOC is 100% compatible to hard disk and DOS.

Customer don't need any extra software utility. It is just "plug and play", easy and reliable.

Right now the DOC is available in 2MB to 72MB capacity.

### • JP5 : DiskOnChip™Memory Address Setting

Address	1-2	3-4	5-6
CE000	CLOSE	OPEN	OPEN
D6000	OPEN	CLOSE	OPEN
DE000	OPEN	OPEN	CLOSE

---

## 2.5 COM2 RI Pin Setting

The COM2 (CN4) can supply +5V or +12V power to the serial devices via RI pin(Pin 9) of the COM port connector. The max. current is 1A with fuse protection for the total two connector's 5V/12V output. If set the output to 12V,customer have to make sure to have 12V to supply to the board.

### • JP12/JP13 : COM2(CN4),Pin 9 RI signal or 5V/12V output selection

Function	JP12	JP13
RI Signal	2-3	1-2
5V	1-2	2-3
12V	1-2	1-2

---

## 2.6 COM2 RS-232, RS-422 or RS-485 Setting

The COM2 (CN4) can be set to RS-232 or RS-422/485 for industrial field site application..

- **JP9/JP10/JP11 : COM2(CN4) RS-232/422/485 setting**

COM2 Function	JP9	JP10	JP11
RS-232	1-2	2-3	1-9 3-10 5-11 7-12
RS-422	2-3	1-2	1-2 3-4 5-6 7-8
RS-485	1-2	1-2	1-2 3-4 5-6 7-8

---

## 2.7 Free IRQ3 and IRQ4 Setting

If customer want to free IRQ3 , IRQ4 for other application. Then have to disable the COM2 (for IRQ3) or disable the COM1(for IRQ4) by BIOS setting. And also have to close the jumper JP15 to free IRQ3 and close the jumper JP16 to free IRQ4.

Release IRQ	JP15	JP16
IRQ3	CLOSE Disable COM2	
IRQ4		CLOSE Disable COM1

# 3

## Connection

This chapter describes how to connect peripherals, switches and indicators to the JUKI-750E board. You can access most of the connectors from the top of the board while it is installed in the chassis.

### 3.1 Floppy Disk Drive Connector

JUKI-750E board comes equipped with a 34-pin daisy-chain driver connector cable. The detailed pin assignment of the connector is specified as following table:

#### • CN7 : FDC CONNECTOR

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	GROUND	2	REDUCE WRITE CURRENT#
3	GROUND	4	N/C
5	GROUND	6	N/C
7	GROUND	8	INDEX#
9	GROUND	10	MOTOR ENABLE A#
11	GROUND	12	DRIVE SELECT B#
13	GROUND	14	DRIVE SELECT A#
15	GROUND	16	MOTOR ENABLE B#
17	GROUND	18	DIRECTION#
19	GROUND	20	STEP#
21	GROUND	22	WRITE DATA#
23	GROUND	24	WRITE GATE#
25	GROUND	26	TRACK 0#
27	GROUND	28	WRITE PROTECT#
29	GROUND	30	READ DATA#
31	GROUND	32	SIDE 1 SELECT#
33	GROUND	34	DISK CHANGE#

---

## 3.2 IDE Disk Drive Connector

You can attach two IDE( Integrated Device Electronics) hard disk drives to the JUKI-750E internal controller. The board comes equipped with a 40-pin flat-cable connector. The detailed pin assignment of the connector is specified as following table:

### • CN9: IDE Interface Connector

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	RESET#	2	GROUND
3	DATA 7	4	DATA 8
5	DATA 6	6	DATA 9
7	DATA 5	8	DATA 10
9	DATA 4	10	DATA 11
11	DATA 3	12	DATA 12
13	DATA 2	14	DATA 13
15	DATA 1	16	DATA 14
17	DATA 0	18	DATA 15
19	GROUND	20	N/C
21	N/C	22	GROUND
23	IOW#	24	GROUND
25	IOR#	26	GROUND
27	N/C	28	BALE - DEFAULT
29	N/C	30	GROUND - DEFAULT
31	INTERRUPT	32	IOCS16#-DEFAULT
33	SA1	34	N/C
35	SA0	36	SA2
37	HDC CS0#	38	HDC CS1#
39	HDD ACTIVE#	40	GROUND

---

## 3.3 Parallel Port

This port is usually connected to a printer, The JUKI-750E includes an on-board parallel port, accessed through a 26-pin flat-cable connector CN8. The detailed pin assignment of the connector is specified as following table:

• **CN8 : Parallel Port Connector**

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	STROBE#	2	DATA 0
3	DATA 1	4	DATA 2
5	DATA 3	6	DATA 4
7	DATA 5	8	DATA 6
9	DATA 7	10	ACKNOWLEDGE
11	BUSY	12	PAPER EMPTY
13	PRINTER SELECT	14	AUTO FORM FEED #
15	ERROR#	16	INITIALIZE
17	PRINTER SELECT LN#	18	GROUND
19	GROUND	20	GROUND
21	GROUND	22	GROUND
23	IOW#	24	GROUND
25	GROUND		

### 3.4 Serial Ports

The JUKI-750E offers two high speed NS16C550 compatible UARTs with Read/Receive 16 byte FIFO serial ports. These ports let you connect to serial devices or a communication network. One DB-9 connector and three 10-pin headers are provided by the JUKI-750E. The detailed pin assignment of the connectors are specified as following tables:

• **COM1(CN5) : Serial Port Connector**

PIN NO.	DESCRIPTION
1	DATA CARRIER DETECT (DCD)
2	RECEIVE DATA (RXD)
3	TRANSMIT DATA (TXD)
4	DATA TERMINAL READY (DTR)
5	GROUND (GND)
6	DATA SET READY (DSR)
7	REQUEST TO SEND (RTS)
8	CLEAR TO SEND (CTS)
9	RING INDICATOR (RI)

• **COM2(CN4) : 2x5-pin Header at RS-232 mode**

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	DCD	6	DSR
2	RXD	7	RTS
3	TXD	8	CTS
4	DTR	9	RI
5	GND	10	N/C

• **COM2(CN4) : 2x5-pin Header at RS-422/485 mode**

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	TX-	6	RX+
2	TX+	7	RX-
3		8	
4		9	
5		10	

---

### 3.5 Keyboard/Mouse Connector

The JUKI-750E provides two keyboard connectors. A 5-pin header connector CN16 supports passive backplane applications. Another one is a 6-pin Mini-DIN connector CN16 on the board mounting bracket for single board computer applications.

• **CN16 : 5-pin Header Keyboard Connector**

PIN NO.	DESCRIPTION
1	KEYBOARD CLOCK
2	KEYBOARD DATA
3	N/C
4	GROUND
5	+5V

• **CN1 : 5-pin Header Mouse Connector**

PIN NO.	DESCRIPTION
1	MOUSE DATA
2	N/C
3	GROUND
4	+5V
5	MOUSE CLOCK



• **CN2 : 6-pin Mini-DIN Keyboard/Mouse Connector**

PIN NO.	CN15 keyboard
1	KEYBOARD DATA
2	MOUSE DATA
3	GROUND
4	+5V
5	KEYBOARD CLOCK
6	MOUSE CLOCK

---

### 3.6 External Switches and Indicators

There are many external switches and indicators for monitoring and controlling your CPU board. These features are completely optional install them if you need them. The detailed pin assignment of the connectors is specified as following table:

• **CN3 : RESET BUTTON**

PIN NO.	DESCRIPTION
1	EXTERNAL RESET
2	GROUND

• **CN10 : IDE LED connector**

PIN-NO	DESCRIPTION
1	HDD ACTIVE#
2	+5V

---

### 3.7 External Power Connector

The JUKI-750E has an on-board external power connector CN6. You can connect power directly to the CPU board for some single-board-computer( without passive backplane) application.

• **CN6 : EXTERNAL POWER CONNECTOR**

PIN NO.	DESCRIPTION
1	+5V
2	+12V
3	-12V
4	GROUND
5	GROUND
6	-5V
7	+12V
8	+5V

---

### 3.8 External Speaker

The JUKI-750E has its own buzzer, you also can connect to the external speaker through the connector CN18 :

• **CN18 : SPEAKER**

PIN NO.	DESCRIPTION
1	SPEAKER SIGNAL
2	+5V

---

### 3.9 PC/104 Connection Bus

The JUKI-750E's PC/104 expansion bus let you attach any kind of PC/104 modules. The PC/104 bus is already become the industrial embedded PC bus standard, so you could easily install over thousands of PC/104 modules from hundreds of venders in the world.

**NOTE : JUKI-750E allows directly plug in PC/104 module, don't need PC/104 Connection Kit.**

---

### 3.10 VGA/LCD Interface Connector

The JUKI-750E provides a 2x22-pin connector for the LCD flat panel interface and a DB15 VGA connector.

• **CN13 : 15-pin Female Connector**

1	RED	2	GREEN
3	BLUE	4	NC
5	GROUND	6	GROUND
7	GROUND	8	GROUND
9	NC	10	GROUND
11	NC	12	NC
13	HSYNC	14	VSYNC
15	NC		

• **CN14: LCD Interface Connector**

PIN NO.	DESCRIPTION	PIN NO.	DESCRIPTION
1	+12V	2	+12V
3	GND	4	GND
5	+5V	6	+5V
7	FPVEE	8	GND
9	P0	10	P1
11	P2	12	P3
13	P4	14	P5
15	P6	16	P7
17	P8	18	P9
19	P10	20	P11
21	P12	22	P13
23	P14	24	P15
25	P16	26	P17
27	P18	28	P19
29	P20	30	P21
31	P22	32	P23
33	GND	34	GND
35	SHFCLK	36	FLM
37	M	38	LP
39	GND	40	ENABLK
41	GND	42	N/C
43	+5V	44	5V

---

### 3.11 Lan RJ45 Connector

The ROCKY-750E built-in a RJ45 Lan connector for 10Mbps Ethernet(NE-2000 compatible) operation.

• **CN15 : Lan RJ45 Connector**

1	TX+	5.	NC
2	TX-	6.	RX-
3.	RX+	7.	NC
4.	NC	8.	NC

• **CN17 : LED Connector(4-pin header) for Lan**

1	LED Link	2	+5V
3	LED RX	4	+5V

# 4

## AMI BIOS Setup

The JUKI-750E use AMI BIOS for system configuration, and the AMI BIOS setup program is designed to provide maximum flexibility in configuring the system by offering various options which may be selected for end-user requirements. This chapter is written to assist you in the proper usage of these features.

---

### 4.1 Getting Start

When the system is powered on, the BIOS will enter the Power-On-Self-Test routines. These routines will be executed for System Test and Initialization and System Configuration Verification. After the POST routines are completed, the following message appears :

**" Hit < Del>, if you want to run SETUP"**

To access AMI BIOS Setup program, press <Del> key.

---

### 4.2 Standard CMOS Setup

Standard CMOS Setup is the first option on the main menu. The standard CMOS setup utility is used to configure the following features :

- i Date/Time,
- i Hard Disk Type,
- i Floppy Disk Type,

All of these features are almost the same as common, so we do not describe more detailed in here.

---

### 4.3 Peripheral Setup

When you enter the Peripheral Setup, you may see the following items for customer's setting.:

- j On-board IDE : The IDE hard disk drive can be **Enable** or **Disable** by this item. When you do not need hard disk, the IDE controller can be disabled.
- j On-board FDC : The floppy disk drive can be **Enable** or **Disable** by this item. When you do not need floppy disk, the FDD controller can be disabled.
- j Serial Port 1 : The options are **Disable**, **3E8,2F8**, or **3F8**. You can set the I/O address of the serial port ( COMA) or disable it.
- j Serial Port 2 : The options are **Disable**, **2E8,3F8**, or **2F8**. You can set the I/O address of the serial port 1 ( COMB) or disable it.
- j Parallel Port : The options are **Disable**, **3BC**, **378** or **278**. You can set the I/O address of the parallel port or disable it.
- j Parallel Port Mode : ROCKY-318 provides **EPP,ECP,ECP+EPP**, and **Normal Mode**.

# Appendix A. Watch-Dog Timer

The Watch-Dog Timer is provided to ensure that standalone systems can always recover from catastrophic conditions that caused the CPU to crash. This condition may have occurred by external EMI or a software bug. When the CPU stops working correctly, hardware on the board will either perform a hardware reset (cold boot) or a non-maskable interrupt (NMI) to bring the system back to a known state.

The Watch-Dog Timer is controlled by two I/O ports.

443 (hex)	Read	Enable the refresh the Watch-Dog Timer.
843 (hex)	Read	Disable the Watch-Dog Timer.

To enable the Watch-Dog Timer, a read from I/O port 443H must be performed. This will enable and activate the countdown timer which will eventually time out and either reset the CPU or cause an NMI depending on the setting of JP3. To ensure that this reset condition does not occur, the Watch-Dog Timer must be periodically refreshed by reading the same I/O port 443H. This must be done within the time out period that is selected by jumper JP4.

A tolerance of at least 30% must be maintained to avoid unknown routines within the operating system (DOS), such as disk I/O that can be very time consuming. Therefore if the time out period has been set to 10 seconds, the I/O port 443H must be read within 7 seconds.

---

Note: when exiting a program it is necessary to disable the Watch-Dog Timer, otherwise the system will reset.

---

# Appendix B. Panel Support List

The JUKI-750E supports a wide range flat panels. The different flat panel will need different LCD drive BIOS. The default setting is for Color DSTN flat panel. The available BIOS for different panels are in the following list. Please note all the BIOS files already included the system BIOS and LCD drive BIOS, customer only need to re-program the BIOS flash chip with the file, then power on again.

**11MLCD.ROM – BIOS for MONO DSTN 640x480**

For example : HOSIDEN HLM6667  
HITACHI LMG5160XUFC  
CASIO MD650TS00-01  
OPTREX DMF\_50260NFU-FW-8

**11DSTN.ROM – BIOS for Color DSTN 640x480**

For example : SANYO LCM-5331-22NTK  
SHARP LM64C35P

**11TFTS1.ROM – BIOS for TFT 640x480-SYNC (16-bit)**

**11TFTS2.ROM – BIOS for TFT 640x480-SYNC (18/24-bit)**

For example : HITACHI TX26D60/TX24D55  
TOSHIBA LTM09C015A  
SHARP LQ10D321

**11TFTLP1.ROM – BIOS for TFT 640x480-LP(16-bit)**

**11TFTLP2.ROM – BIOS for TFT 640x480-LP(16/24-bit)**

For example : TOSHIBA LTM09C015A18

**11TFT861.ROM – BIOS for TFT 800x600-SYNC(16-bit)/**

**11TFT862.ROM – BIOS for TFT 800x600-SYNC(18/24-bit)**

For example : NEC NL8060AC26-05  
NEC NL8060AC26-04  
NEC NL8060BC31-02

**11EL.ROM – BIOS for EL 640x480**

For example : PLANAR EL640.480-A

**11PLASMA.ROM – BIOS for PLASMA 640x480**

For example : PANASONIC S817

## How to update the BIOS by yourself ?

1. Use EPROM Programmer setting the right Flash type and then write the file into the Flash.

To use this method, you should carefully take the Flash chip out of socket and then put it back after finish the programming.

Usually the flash type is : ATMEL AT29C010A

**Or,**

2. There also have a utility (**FLASH631.COM**) and directly re-program the BIOS under DOS.

For example :

```
C:>FLASH631 11MLCD.ROM
```



# Appendix C. I/O Information

## IO Address Map

<b>I/O address Range</b>	<b>Description</b>
000-01F	DMA Controller #1
020-021	Interrupt Controller #1, Master
040-05F	8254 timer
060-06F	8042 (Keyboard Controller)
070-07F	Real time Clock, NMI (non-maskable interrupt) Mask
080-09F	DMA Page Register
0A0-0BF	Interrupt Controller #2
0C0-0DF	DMA Controller #2
0F0	Clear Math Coprocessor Busy
0F1	Reset Math Coprocessor
0F2	Core logic programming configuration
0F8-0FF	Math Coprocessor
1F0-1F8	Fixed Disk
200-207	Game I/O
278-27F	Parallel Printer Port 2 (LPT3)
2E8-2EF	Serial Port 4
2F8-2FF	Serial Port 2
300-31F	Prototype Card
360-36F	Reserved
378-37F	Parallel Printer Port 1 (LPT2)
3B0-3BF	Monochrome Display and Printer Adapter (LPT1)
3C0-3CF	Reserved
3D0-3DF	Color/Graphics Monitor Adapter
3E8-3EF	Serial Port 3
3F0-3F7	Diskette Controller
3F8-3FF	Serial Port 1
443	Watch dog timer enable
843 or 043	Watch dog timer disable

## 1st MB Memory Address Map

Memory address	Description
00000-9FFFF	System memory
A0000-BFFFF	VGA buffer
C0000-C7FFF	VGA BIOS
C8000 – EFFFF	Free for customer application
F0000-FFFFF	System BIOS
1000000-	Extend BIOS

## IRQ Mapping Chart

IRQ0	System Timer	IRQ8	RTC Clock
IRQ1	Keyboard	IRQ9	Unused
IRQ2	Cascade to IRQ Controller	IRQ10	Unused
IRQ3	COM2/COM4	IRQ11	Unused
IRQ4	COM1/COM3	IRQ12	PS/2 mouse
IRQ5	Unused	IRQ13	FPU
IRQ6	FDC	IRQ14	Primary IDE
IRQ7	Printer	IRQ15	Unused

## DMA Channel Assignments

DMA Channel	Function
0	Available
1	Available
2	Floppy Disk
3	Available
4	Cascade for DMA controller 1
5	Available
6	Available
7	Available